



Certified Capability List

This Capability List is based on a certification session performed by the *TALQ Certification Tool (v2.4.1-update.10)* on 2022-10-19 23:35:31.894 +0000.

The Capability List is a consolidated list of TALQ features which are implemented in a product.

The tool has succesfully performed 26 tests.

Product details

Product Name RFLight2_gtwy

Company Hispaled Hispanica del led S.L.

Type GATEWAY

Notes

Generated on 2022-10-19 23:35:31.894 +0000

Supported profiles • Lighting

API version certified: 2.4.1

Certification performed by app version: 2.4.1-update.10

Capability list

Security

Enabled ✓

Functions

Basic

The Basic function describes the properties related to the physical asset to which the logical device is associated, such as identification (assetId) and location information.

Attributes

#	Attribute	Description
✓	swVersion	Software version installed on the device.
✓	currentTime	Current time of the device defined as local time with time zone designator. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new TimeFunction.currentTime instead.]

Events

#	Event type	Description
✓	deviceReset	The physical device containing the logical device was reset

Gateway

The Gateway function includes the necessary attributes to enable the communication between the CMS and the Gateway according to the TALQ Specification.

Attributes

#	Attribute	Description
✓	cmsUri	Base URI for TALQ communication that allows the Gateway to access the CMS. Must be an absolute URI. Other URI's for accessing CMS can be relative to this base.
✓	cmsAddress	CMS UUID address
✓	gatewayUri	Base URI for TALQ communication that allows the CMS to access the Gateway. Must be an absolute URI. Other URI's for accessing Gateway can be relative to this base.
✓	gatewayAddress	Gateway UUID address
✓	retryPeriod	Time duration before the Gateway retransmits a message for which expected response has not been received.

- | | |
|----------|---|
| ✓ crlUrn | URI where the Gateway can obtain the Certification Revocation List (CRL). |
| ✓ vendor | Vendor identification. |

Lamp Actuator

The Lamp Actuator function includes attributes related to lighting control and it represents the smallest unit for control purposes. In practice, however, a Lamp Actuator function can control combinations of several lamps and control gear but all in the same way, as if they are all one individual unit.

Attributes

#	Attribute	Description
✓	defaultLightState	Sets the default light output for the lamp actuator. This shall be applicable if no other command is active. This attribute shall be set to 100% as default value.
✓	targetLightCommand	Latest command for the lamp actuator.
✓	feedbackLightCommand	This attribute reflects the command in effect and it might deviate from the actualLightState due to propagation time or due to internal ODN specific mechanisms to handle the priority of the requests.
✓	actualLightState	This attribute should reflect the physical state of the light source as much as possible, including factors such as CLO. It may be calculated or measured, depending on the specific ODN implementation, which is outside the scope of this specification.
✓	calendarID	TALQ Address of the calendar controlling this lamp actuator. If this attribute is empty, the behavior shall be determined by the ODN. If the attribute is invalid, the ODN shall trigger a generic invalid address event and the behavior shall be determined by the ODN.

Events

#	Event type	Description
✓	lightStateChange	Light state has changed

Lamp Monitor

The Lamp Monitor function enables monitoring of lamp parameters. A Lamp Monitor function should be associated with a specific lamp/control gear combination. Multiple lamp monitor functions may be implemented by a single device.

Attributes

#	Attribute	Description
✓	supplyVoltage	RMS supply volts when supplyType is AC, supply voltage (V) when supplyType is DC.
✓	supplyCurrent	RMS supply current (A) when supplyType is AC, supply current (A) when supplyType is DC.
✓	activePower	Active power.
✓	reactivePower	Reactive power.
✓	powerFactor	Active power/Apparent power.
✓	lampFailure	The lamp is not operating as it is supposed to (e.g. the lamp is broken). This event shall be used to detect a situation where the lamp (or LED module(s)) should be lit, but produce no light. This could be detected by the current flowing or power consumed.
✓	currentTooHigh	Supply current is above the highCurrentThreshold defined in the lamp type.
✓	currentTooLow	Supply current is below the lowCurrentThreshold defined in the lamp type.
✓	supplyVoltageTooHigh	Level of supply voltage is above the highLampVoltageThreshold.
✓	supplyVoltageTooLow	Level of supply voltage is below the lowSupplyVoltageThreshold.
✓	highSupplyVoltageThreshold	Supply voltage above which the supplyVoltageTooHigh event is triggered.
✓	lowSupplyVoltageThreshold	Supply voltage below which the supplyVoltageTooLow event is triggered.

Events

#	Event type	Description
✓	currentTooHigh	Supply current is above the highCurrentThreshold defined in the lamp type
✓	currentTooLow	Supply current is below the lowCurrentThreshold defined in the lamp type

- ✓ lampFailure The lamp is not operating as it is supposed to

- ✓ supplyVoltageTooHigh Level of supply voltage is above the highLampVoltageThreshold.

- ✓ supplyVoltageTooLow Level of supply voltage is below the lowSupplyVoltageThreshold.

Services

Configuration Service

The TALQ Configuration Service enables discovery and configuration of devices and services

Options

#	Option	Value	Description
---	--------	-------	-------------

Control Service

The Control service describes the mechanisms to operate the actuator functions in order to enable schedule based and override control

Options

#	Option	Value	Description
---	--------	-------	-------------

Events

#	Event Type	Description
✓	invalidCalendar	An invalid calendar has been provided by the CMS to the ODN
✓	invalidProgram	A control program has been provided by the CMS, which cannot be implemented by the ODN

Data Collection Service

The TALQ Data Collection Service is a provision to configure how ODN measurements, status information and events are logged, and when or under what conditions the logged data is

transferred to the CMS

Options

#	Option	Value	Description
✓	supportedModes	<ul style="list-style-type: none"> VendorRecordingMode EventRecordingMode ImmediateReportingMode 	Recording and Reporting modes supported

Events

#	Event Type	Description
✓	invalidLoggerConfig	The CMS has provided a data logger configuration that cannot be implemented by the ODN

On Demand Data Request Service

This service provides the mechanism to access attributes in the logical devices by requesting attribute values from the ODN

Objects

Event log data

Properties

#	Property	Description
✓	eventType	Identifier of event reported
✓	srcAddress	Address of Logical device or function within a logical device which is the source of the event or to which this event applies

Command


Properties

#	Property	Description
---	----------	-------------

- | | |
|------------|---|
| ✓ state | Light state to be applied to the lamp actuator |
| ✓ cmsRefId | CMS reference, which can be used for data logging |

: The Certification Test Tool is designed to provide a high level of confidence that complementary systems can communicate successfully. As both the protocol and the test tool evolve, all mandatory and other core tests are confirmed by comparison with real-life scenarios (plug-fest or similar). Some tests of optional and more peripheral features may not yet have been confirmed in this way; such features are identified with an asterisk ().

This Capability List is based on a certification session performed by the TALQ Certification Tool (v2.4.1-update.10) on 2022-10-19 23:35:31.894 +0000.

 and **TALQ** are trademarks owned by the TALQ Consortium.

© TALQ Consortium

