



Certified Capability List

This Capability List is based on a certification session performed by the *TALQ Certification Tool (v2.6.3-online.2-tmp)* on 2025-09-05 12:51:46.334 +0200.

The Capability List is a consolidated list of TALQ features which are implemented in a product.

The tool has succesfully performed 37 tests.

Product details

Product Name	Sustainer Brokerage Layer
Company	Sustainer
Type	GATEWAY
Notes	
Generated on	2025-09-05 12:51:46.334 +0200
Supported profiles	Lighting
API version certified:	2.6.3
Certification performed by app version:	2.6.3-online.2-tmp

Functional tests

The Functional Tests help customers understand the capabilities of a TALQ-certified product. All functional test cases are presented to provide comprehensive context, and successful completion of each test is indicated with a tick mark. Each Functional Test is related to a set of required TALQ technical test cases.

Configuring	4 of 11
Support light point control features	✓
The Gateway successfully connects to a CMS and transmits its capabilities for light point control features and services.	CFG-1

Support cabinet control lighting features

The Gateway successfully connects to a CMS and transmits its capabilities for cabinet control lighting features and services.

CFG-2**Support sensor-based light point control features**

The Gateway successfully connects to a CMS and transmits its capabilities for sensor-based light point control features and services.

CFG-3**Discovery of the network of devices**

✓

The Gateway transmits all its devices to the CMS together with their configuration and asset information.

CFG-4**Initialize light point electrical alarm thresholds**

✓

The Gateway is able to receive the light point electrical alarm thresholds from the CMS, including Lamp Voltage Too High/Low, Lamp Current Too High/Low, Active Power Too High/Low and Power Factor Too Low

CFG-5**Initialize and change the cabinet control alarm thresholds**

✓

The Gateway is able to receive the cabinet control electrical alarm thresholds from the CMS, including < to be defined >

CFG-6**Initialize and change the light point parameters**

The Gateway is able to receive the light point parameters from the CMS.

CFG-7**Initialize and change a group of luminaires**

The Gateway is able to handle a command from the CMS to set or change a group of light points to assign them a control program.

CFG-8**Change the sampling frequency for measurements**

The Gateway is able to change the sampling of measurements and properly reflected in the next data log sent to the CMS.

CFG-9**Change the reporting frequency for measurements**

The Gateway is able to change the reporting frequency (how often it sends data logs to the CSM) for measurements.

CFG-10

Update the firmware of the hardware devices

The Gateway supports data package service and accepts a data package to update firmware on a physical device.

CFG-11

Monitoring

1 of 11

Measure and report basic electrical values (Current/Voltage/Active Power/Power Factor)

The Gateways sends "valid values" for electrical values including mains voltage, current, active power and power factor to the CMS using one of the data logging service.

MTG-1

Measure and report cumulating energy counter

The Gateways sends "valid growing values" for energy counter to the CMS using one of the data logging service.

MTG-2

Report lamps' number of operating hours

The Gateways sends "valid growing values" for lamp operating hours counter to the CMS using one of the data logging service.

MTG-3

Report lamps' number of switch-on counter

The Gateways sends "valid growing values" for lamp switch-on counter to the CMS using one of the data logging service.

MTG-4

Report lamps' number of supply loss counter

The Gateways sends "valid growing values" for supply loss count to the CMS using one of the data logging service.

MTG-5

Monitor the lamp level feedback when a manual override command is sent

✓

The Gateway receives a manual override command, sends it to the device and can report, using on-demand read as well as a data logger service, that the lamp level feedback is getting close to the command.

MTG-6

Report temperature

The Gateways sends temperature values to the CMS using one of the data logging service.

MTG-8

Report presence detection

The Gateways sends presence detection values to the CMS using one of the data logging service.

MTG-9

Report noise level	
The Gateways sends noise level values to the CMS using one of the data logging service.	MTG-10

Report light level	
The Gateways sends light level values to the CMS using one of the data logging service.	MTG-11

Report firmware updating process	
The Gateway is able to report the firmware update events	MTG-12

Controlling	1 of 7
-------------	--------

Manual control over a light point		✓
The Gateway properly receives and handles a manual override command sent by the CMS for one single light point	CTR-1	

Manual control over a group of light points	
The Gateway properly receives and handles a manual override command sent by the CMS for a group of light points	CTR-2

Manual control with a delay	
The Gateway properly receives and handles a manual override command that includes a delay, sent by the CMS for one single light point.	CTR-3

Manual control with a ramp	
The Gateway properly receives and handles a manual override command that includes a rampup, sent by the CMS for one single light point.	CTR-4

Automatic switch light on/off based on photocell value	
The Gateway can properly execute a control program that switches the light ON and OFF based on a local photocell value on a single light point.	CTR-5

Automatic change of light level when presence detected	
	CTR-6

The Gateway can properly execute a control program that changes the light dimming level based on a local presence sensor on a single light point.

Automatic change of light level when noise detected

The Gateway can properly execute a control program that changes the light dimming level based on a local noise sensor on a single light point. **CTR-7**

Alarming

3 of 5

Report lighting alarms to the CMS



The Gateway can produce lighting alarms and send them to the CMS using one of the data logger services. **ALR-1**

Report electrical alarms to the CMS



The Gateway can produce electrical alarms and send them to the CMS using one of the data logger services. **ALR-2**

Report invalid program and calendar

The Gateway can produce invalid calendar and control program alarms and send them to the CMS using one of the data logger services. **ALR-3**

Report activity for sensor based lighting

The Gateway can send an event in case of activity detected and send them to the CMS using one of the data logger services. **ALR-4**

Request the status of the alarm



The Gateway can report the status of the alarms as a response to a request from the CMS **ALR-5**

Programming

5 of 9

Fix time switching+dimming control program that applies to all days in the year



The Gateway can receive and execute a control program that switches and dims a light point at fix time all days in the year. **PRG-1**

Astro-clock switching + fix time dimming control program that applies to all days in the year

PRG-2

The Gateway can receive and execute a control program that switches a light point at sunrise/sunset +/- few minutes and dim it during an astro-clock active period, all days in the year.

Photocell switching + fix time dimming control program that applies to all days in the year

The Gateway can receive and execute a control program that switches a light point when photocell indicates darkness and dim it during the photocell active period, all days in the year.

PRG-3

Photocell and astro-clock switching + fix time dimming control program that applies to all days in the year

The Gateway can receive and execute a control program that switches a light point when photocell indicates darkness or at sunrise/sunset +/- few minutes (the earlier for switch ON/OFF) and dim it during the photocell active period, all days in the year.

PRG-4

Part night switching program



The Gateway can receive and execute a control program that switches a light point OFF at fixed time in the middle of the night.

PRG-5

Support exceptional periods (e.g., Sept 10th to Oct 16th)



The Gateway can receive and execute a calendar that has a default rule for all days in the year and another higher priority calendar that applies from DAY 1 to DAY 2.

PRG-6

Support exceptional week days (e.g., every Saturday and Sunday)



The Gateway can receive and execute a calendar that has a default rule for all days in the year and another higher priority calendar that applies every Saturday night and Sunday night, every day in the year.

PRG-7

Support exceptional week days (e.g., every Saturday and Sunday) and exceptional periods (e.g., Sept 10th to Oct 16th)



The Gateway can receive and execute a calendar that has a default rule for all days in the year, another higher priority calendar that applies every Saturday night and Sunday night, every day in the year and another higher priority calendar that applies to every saturday between DAY 1 and DAY 2.

PRG-8

Support dynamic lighting program based on sensor detection

The Gateway can receive and execute a control program that has rule based on presence sensor.

PRG-9

Capability list

Security

Enabled ✓

Functions

Basic

The Basic function describes the properties related to the physical asset to which the logical device is associated, such as identification (assetId) and location information.

Attributes

#	Attribute	Description
✓	displayName	Display name of the asset.
✓	assetId	Customer identifier of the asset. If multiple devices have the same assetId it means they belong to the same asset.
✓	swVersion	Software version installed on the device.
✓	installationDate	The installation date of Physical Device.
✓	location	Latitude, Longitude and Altitude. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new LocationSensorFunction.location instead.]
✓	timeZone	Time zone of the device. Time zone may be expressed in two formats. <timezone> where <timezone> is a time zone as defined in the zone.tab of the IANA timezone database [IANA]; and stdoffset[dst[offset][,start[/time],end[/time]]] as defined by the Open Group for posix systems [POSIX]. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new TimeFunction.timeZone instead.]
✓	currentTime	Current time of the device defined as local time with time zone designator. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new TimeFunction.currentTime instead.]
✓	operatingHours	Number of operating hours of the device.

Events

#	Event type	Description
✓	deviceReset	The physical device containing the logical device was reset

Communication

The Communication Function contains attributes related to the communication within the ODN, and between ODN devices and Gateways. Although communication within the ODN is outside the scope of the TALQ Smart City Protocol, this Function enables access to a minimum set of configuration and state information of the ODN communication interface in order to facilitate system management from the CMS.

Attributes

#	Attribute	Description
✓	physicalAddress	Physical address of the device. For example, IEEE MAC address. This attribute can be used to map between logical and physical devices. The format is specific to the ODN implementation.

Events

#	Event type	Description
✓	communicationFailure	This event is generated by the ODN when the communication function is not operating as expected

Gateway

The Gateway function includes the necessary attributes to enable the communication between the CMS and the Gateway according to the TALQ Specification.

Attributes

#	Attribute	Description
✓	cmsUri	Base URI for TALQ communication that allows the Gateway to access the CMS. Must be an absolute URI. Other URI's for accessing CMS can be relative to this base.
✓	cmsAddress	CMS UUID address
✓	gatewayUri	Base URI for TALQ communication that allows the CMS to access the Gateway. Must be an absolute URI. Other URI's for accessing Gateway can be relative to this base.
✓	gatewayAddress	Gateway UUID address
✓	retryPeriod	Time duration before the Gateway retransmits a message for which expected response has not been received. [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new GatewayFunction.gatewayRetryPeriod instead.]
✓	crlUrn	URI where the Gateway can obtain the Certification Revocation List (CRL).
✓	vendor	Vendor identification.

Lamp Actuator

The Lamp Actuator function includes attributes related to lighting control and it represents the smallest unit for control purposes. In practice, however, a Lamp Actuator function can control combinations of several lamps and control gear but all in the same way, as if they are all one individual unit.

Attributes

#	Attribute	Description
---	-----------	-------------

✓ standbyMode	Defines the behavior of the lamp actuator when output level is set to zero. If OFF, light output level is zero with no power to the lamp control gear. If ON, light output level is zero but power is delivered to the lamp control gear (standby mode).
✓ cloEnabled	Determines whether a Constant Light Output (CLO) correction factor is used. CLO is used to compensate for lumen output degradation over the life time of the lamp. If CLO is enabled, lamps are dimmed part of the lampType.
✓ defaultLightState	Sets the default light output for the lamp actuator. This shall be applicable if no other command is active. This attribute shall be set to 100% as default value.
✓ targetLightCommand	Latest command for the lamp actuator.
✓ feedbackLightCommand	This attribute reflects the command in effect and it might deviate from the actualLightState due to propagation time or due to internal ODN specific mechanisms to handle the priority of the requests.
✓ actualLightState	This attribute should reflect the physical state of the light source as much as possible, including factors such as CLO. It may be calculated or measured, depending on the specific ODN implementation, which is outside the scope of this specification.
✓ calendarID	TALQ Address of the calendar controlling this lamp actuator. If this attribute is empty, the behavior shall be determined by the ODN. If the attribute is invalid, the ODN shall trigger a generic invalid address event and the behavior shall be determined by the ODN.

Events

#	Event type	Description
✓	lightStateChange	Light state has changed

Lamp Monitor

The Lamp Monitor function enables monitoring of lamp parameters. A Lamp Monitor function should be associated with a specific lamp/control gear combination. Multiple lamp monitor functions may be implemented by a single device.

Attributes

#	Attribute	Description
✓	operatingHours	Number of hours the lamp is on. This is the value used in CLO and may be set by the CMS.
✓	activePower	Active power.
✓	activeEnergy	Cumulative active energy (since installation or counter reset).

Events

#	Event type	Description
✓	lampFailure	The lamp is not operating as it is supposed to (e.g. the lamp is broken). This event shall be used to detect a situation where the lamp (or LED module(s)) should be lit, but produce no light. This could be detected by the current flowing or power consumed.

Electrical Meter

The electrical meter function supports electrical metering capabilities including measurements of voltage, current, power, energy, and power factor. This function may be associated with Luminaire Controllers, Cabinet Controllers or electrical meters installed in switch boxes. ODNs may implement both single phase and three phase meters. Typically meters within a control device will be single phase and stand-alone meters. A street side cabinet may have single phase or three phase meters.

Attributes

#	Attribute	Description
✓	totalPower	Sum of the active power consumed on phase 1, 2 and 3, or just the power for a single phase meter.
✓	totalActiveEnergy	Total cumulative kWh measured by the meter since installation date (or counter reset).

Events

#	Event type	Description
---	------------	-------------

Services

Configuration Service

The TALQ Configuration Service enables discovery and configuration of devices and services

Options

#	Option	Value	Description
✓	commissioningSupported*		This ODN can support commissioning from the CMS side.
✓	devicesPaginationSupported*		This ODN can support pagination of devices.

Control Service

The Control service describes the mechanisms to operate the actuator functions in order to enable schedule based and override control

Options

#	Option	Value	Description
✓	supportedTypes	- AbsoluteActivePeriod - ccDay*	Control Program and calendar options supported are defined by announcing support for the given modes
✓	maxProgramsPerCalendar		Maximum number of control programs per calendar
✓	maxSwitchPointsPerProgram		Maximum number of switching points per control program

✓ maxActivePeriodsPerProgram		Maximum number of active periods per control program
✓ dayOffset	• 0	Offset of start of day
✓ ccDaySupport	• n • o • O • c • c • u • r • r • e • n • c • e • s	Indicates the ccDay options supported
✓ programSecondsSupported*		Indicates whether the field of seconds is supported in programs.

Events

#	Event Type	Description
✓	invalidCalendar	An invalid calendar has been provided by the CMS to the ODN
✓	invalidProgram	A control program has been provided by the CMS, which cannot be implemented by the ODN

Data Collection Service

The TALQ Data Collection Service is a provision to configure how ODN measurements, status information and events are logged, and when or under what conditions the logged data is transferred to the CMS

Options

#	Option	Value	Description
✓	supportedModes	• EventRecordingMode • ImmediateReportingMode • VendorRecordingMode	Recording and Reporting modes supported
✓	samplingAccuracy		Maximum deviation of sampling moment in seconds
✓	minCollectionTime		Base time between sampling and being able to report attributes specified in a data logger

✓ loggableAttributes	sustainer_lcm/lampActuatorAll/light_state_change	List of descriptions of the attributes within device classes that can be logged using periodic recording
✓ samplingPeriodSupported		Indicates whether the ODN supports periodic sampling for a data logger in periodic recording mode
✓ attributeScopeSupported		Indicates whether the ODN supports filtering attributes by scope (attributeScope); for a data logger in periodic or vendor recording mode.
✓ recordingActivePeriodSupported		Indicates whether the ODN supports active periods for a data logger in recording modes

Events

#	Event Type	Description
✓	invalidLoggerConfig	The CMS has provided a data logger configuration that cannot be implemented by the ODN

On Demand Data Request Service

This service provides the mechanism to access attributes in the logical devices by requesting attribute values from the ODN

Objects

Luminaire Type

The LuminaireType consists of a set of attributes that together characterize, i.e.: are generic for, a given luminaire, excluding the concept of Controller, Driver and Bracket.

Properties

#	Property	Description
✓	address	TALQ address of the Luminaire Type
✓	name	Descriptive name of the LuminaireType
✓	gtin	Global Trade Item Number of luminaire
✓	manufacturerName	Name of manufacturer
✓	productFamily	Product family name of luminaire
✓	model	Product model of luminaire
✓	maximumLuminousFluxOutput	Maximum Light Output luminous flux output
✓	minimumLuminousFluxOutput	Minimum Light Output of the luminaire
✓	lightSourceType	Light source type.
✓	lightDistributionType	Enumeration of possible light distribution type, using the Zhaga D4i enumeration. Please refer to ZD4i standard for more details.
✓	maximumPower	Maximum power that the Luminaire can operate at
✓	powerAtMinimumDimLevel	Power at minimum dim level for the luminaire.
✓	materialEnclosure	Material of enclosure of the body of the luminaire
✓	materialLightCover	Material of light cover [DEPRECATED: This attribute has been deprecated and it will be removed in the next MAJOR release. Please use the new materialLightCover instead.]
✓	materialLightCover	Material of light cover
✓	luminaireEfficacy	Efficacy of the luminaire
✓	warmUpTime	Sets the delay after a Switch ON command during which the lamp actuator shall not perform any dimming command.
✓	maxOperatingHours	Maximum number of operating hours that the lamp is supposed to live with a given specification. This attribute can be used to set the old lamp attributes when the lamp reaches its expected useful life.
✓	lumenDepreciationCurve	Ordered set of entries (cumulative operating hours, correction factor in %) that form a piece wise linear approximation of the lumen depreciation correction factor curve. The first cumulative hours should be 0 and the last correction factor should be 100%. E.g.: 0 h, 80%; 5000 h, 85%; 10000 h, 90%; 15000 h, 95%; 20000 h, 100%.
✓	cloType	Determines where CLO (Constant Lumen Output) is implemented in the lamp control gear or in the ODN (e.g. control device). This CLO profile is needed even when CLO is implemented by the driver in order to obtain the expected lamp power.
✓	lightSourceManufacturerName	Name of light source manufacturer
✓	lightSourceLedEfficacy	Efficacy of the LED

✓ lor	Light Output Ratio (total light output of the lighting fixture divided by the luminaire flux of the light source) (e.g: 70.5%)
✓ cct	Color temperature of the luminaire (Correlated Color Temperature)
✓ cri	Color rendering index (0 to 100) of the luminaire
✓ backlightCutType	Backwards light blocking solution (e.g: by optics; or reflector; or louvre)

Bracket Type

The BracketType consists of a set of attributes that together characterize, i.e: are generic for, a given Bracket.

Properties

#	Property	Description
✓	address	TALQ address of the Bracket Type
✓	name	Descriptive name of the Bracket Type
✓	manufacturerName	Name of manufacturer
✓	productFamily	Product family name of bracket
✓	model	Product model of bracket

Driver Type

The DriverType consists of a set of attributes that together characterize, i.e. are generic for, a given Driver.

Properties

#	Property	Description
✓	address	TALQ address of the Driver Type
✓	name	Descriptive name of the Driver Type
✓	model	Driver model

Controller Type

The ControllerType consists of a set of attributes that together characterize, i.e. are generic for, a given Controller.

Properties

#	Property	Description
✓	address	TALQ address of the Controller Type
✓	name	Descriptive name of the Controller Type
✓	locationPrecision	Accuracy of the location determination
✓	manufacturerName	Name of manufacturer
✓	productFamily	Product family name of the controller
✓	model	Model of the Controller

✓ mechanicalInterfaces	Type of mechanical connection or socket
✓ electricalInterfaces	The control interface protocol type of the connector of the driver.
✓ protocols	Type of digital communication of the controller

Event log data

Event log data contains a single event, with eventType and value, in each single log entry. It also includes information about whether the log denotes the start or end of the event. Furthermore additional information can be added with the info attribute.

Properties

#	Property	Description
✓	eventType	Identifier of event reported
✓	srcAddress	Address of Logical device or function within a logical device which is the source of the event or to which this event applies

Command

A command defines a type of control action that can be applied to a function. Commands can be generated by a manual override action or by a control program.

Properties

#	Property	Description
✓	state	Light state to be applied to the lamp actuator
✓	cmsRefId	CMS reference, which can be used for data logging. The cmsRefId in a Command is a free text to be used by the CMS for any purpose, e.g: to differentiate contexts. It is a token that allows the CMS to match client requests to the original notification.

✱: The Certification Test Tool is designed to provide a high level of confidence that complementary systems can communicate successfully. As both the protocol and the test tool evolve, all mandatory and other core tests are confirmed by comparison with real-life scenarios (plug-fest or similar). Some tests of optional and more peripheral features may not yet have been confirmed in this way; such features are identified with an asterisk (*).

This Capability List is based on a certification session performed by the TALQ Certification Tool (v2.6.3-online.2-tmp) on 2025-09-05 12:51:46.334 +0200.

 and **TALQ** are trademarks owned by the TALQ Consortium.

 TALQ Consortium

